

IN THE CLAIMS:

Please amend the claims as follows:

1. *(currently amended)* A method for controlling interfrequency handovers of a mobile station, the mobile station comprising a continuous communication mode and a combined slotted communication mode and measurement mode, the method comprising ~~the steps of:~~

-changing the operation of the mobile station into the combined slotted communication mode and measurement mode for preparing an interfrequency handover, if at least a criterion specifying that a quality of a downlink signal relating to a channel on which communication takes place between the mobile station and a mobile communication system in the continuous communication mode is worse than a quality represented by a first target value, is fulfilled,

~~characterized in that~~ wherein the first target value depends on a second target value, the second target value being related to an outer loop power control of a transmission power of the downlink signal.

2. *(currently amended)* A method according to claim 1, further comprising ~~the step of:~~

- updating the first target value at first time instants of those time instants at which the second target value is updated by the power control manner of the transmission power.

3. *(original)* A method according to claim 2, wherein the first target value is updated for every radio frame.

4. *(original)* A method according to claim 2, wherein the first target value is updated for every interleaving period.

5. *(previously presented)* A method according to claim 1, wherein the first target value is equal to the second target value.
6. *(previously presented)* A method according to claim 1, wherein the first target value corresponds to a worse quality than the second target value.
7. *(previously presented)* A method according to claim 1, wherein the value for the quality represented by a first target value is determined for every time slot.
8. *(previously presented)* A method according to claim 1, wherein a further criterion specifies that the criterion is to be fulfilled for a certain first predetermined time period.
9. *(currently amended)* A method according to claim 1, further comprising ~~the step~~ of:
 - estimating adjacent channel interference on the channel on which communication takes place in the continuous communication mode.
10. *(original)* A method according to claim 9, wherein said adjacent channel interference is estimated, if the determined value for the quality represented by a first target value is below a predetermined value.
11. *(currently amended)* A method according to claim 9, further comprising ~~the step~~ of:
 - measuring interference on an adjacent channel in the combined slotted communication and measurement mode.

12. *(currently amended)* A method according to claim 1, further comprising ~~the steps of~~:

- performing an interfrequency handover to a second channel, and
- after entering a continuous mode in the second channel, inhibiting a further interfrequency handover for a certain second predetermined time period.

13. *(currently amended)* A method according to claim 1, further comprising ~~the step of~~:

- performing preparatory measurements for an interfrequency handover in the combined slotted communication mode and measurement mode.

14. *(currently amended)* A method according to claim 13, ~~characterized in that it further comprises the step of~~ comprising:

- in the combined slotted communication mode and measurement mode, synchronizing the mobile station with at least one base station before selection of a target frequency and/or the target base station(s) for the interfrequency handover.

15. *(currently amended)* A method according to claim 14, further comprising ~~the step of~~:

- sending a request ~~(1107, 1108)~~ for the interfrequency handover to the cellular radio system from the mobile station,
- and wherein ~~the step of~~ synchronization is performed after sending the request.

16. *(currently amended)* A method according to claim 14, further comprising ~~the step of~~:

- triggering, based on said preparatory measurements, the synchronization of the mobile station with the at least one base station.

17. *(previously presented)* A method according to claim 14, wherein the mobile station is synchronized in at least one available target frequency with each base station relating to which said preparatory measurements are made.

18. *(previously presented)* A method according to claim 14, wherein the mobile station is synchronized in at least one available target frequency with at least two base stations.

19. *(original)* A method according to claim 18, wherein said at least two base stations belong to the active set of the mobile station.

20. *(original)* A method according to claim 19, wherein the synchronization is performed with all base stations belonging to the active set of the mobile station.

21. *(currently amended)* A method according to claim 19, further comprising the step of:

- performing the interfrequency handover to all base stations belonging to the active set of the mobile station

22. *(currently amended)* A method according to claim 18, ~~characterized in that it further comprises the step of~~ comprising:

- performing the interfrequency handover to said at least two base stations.

23. *(original)* A method according to claim 1, wherein the loop based power control manner is adapted to control the quality of the connection by setting the target value for an inner loop of a closed loop power control.

24. *(currently amended)* A method for controlling an interfrequency handover of a mobile station, the mobile station comprising a continuous communication mode, the method comprising ~~the steps of:~~

- determining a value for a quality factor for a received downlink signal,
~~characterized in that,~~ wherein said interfrequency handover comprises a blind interfrequency handover and the method further comprises ~~the steps of:~~
- comparing the determined quality factor value to a first target value for performing the blind interfrequency handover,
- comparing the determined quality factor value to a second target value, and
- generating power control commands based on the comparison, the first target value being arranged to depend on the second target value and the second value being arranged to relate to an outer loop power control of a transmission power of the downlink signal.

25. *(currently amended)* A mobile station arranged to contain a continuous communication mode and a combined slotted communication and measurement mode, the mobile station comprising:

- ~~means (1207,1212)~~ a measurement block for determining a value for a quality factor for a received downlink signal,
- ~~means (1207,1215)~~ a mode control block for controlling the communication mode of the mobile station,
~~characterized in that~~ wherein the mobile station further comprises
- ~~means (1207,1210)~~ a handover control block for controlling interfrequency handovers, said ~~[[means]]~~ handover control block for controlling interfrequency handover being arranged to compare the determined quality factor value to a first target value for performing the interfrequency handover,
- ~~downlink a power control means (1207,1211)~~ block arranged to compare the determined quality factor value to a second target value and to generate power control

commands based on the comparison, the first target value being arranged to depend on the second target value and the second value being arranged to relate to an outer loop power control of a transmission power of the downlink signal.

26. *(currently amended)* A mobile station according to claim 25, ~~characterized in that it further comprises~~ comprising:

- ~~means (1207,1214)~~ a synchronization control block for synchronizing the mobile station with a base station, said ~~[[means]]~~ synchronization control block arranged to perform the synchronization during the combined slotted communication and measurement mode before selection of a target frequency and/or a target base station(s) for an interfrequency handover.

27. *(currently amended)* A mobile station arranged to contain a continuous communication mode, the mobile station comprising:

- ~~means (1207,1212)~~ a measurement block for determining a value for a quality factor for a received downlink signal,

~~characterized in that the mobile station further comprises~~

- ~~means (1207,1210)~~ a handover control block for controlling blind interfrequency handovers, said ~~means for controlling blind interfrequency handover~~ handover control block being arranged to compare the determined quality factor value to a first target value for performing the blind interfrequency handover,

- ~~downlink~~ a power control ~~means (1207,1214)~~ block arranged to compare the determined quality factor value to a second target value and to generate power control commands based on the comparison, the first target value being arranged to depend on the second target value and the second value being arranged to relate to an outer loop power control of a transmission power of the downlink signal.